

ø99 x H75 (mm)
 Rth 0.25 °C/W
 Power Pd 200 W

MORE PRODUCT DETAILS

IceLED Ultra VS | Lumileds Modular Active Star LED Cooler ø99mm


Mounting Instruction



Lumileds LUXEON COB is a new breakthrough in efficacy for arrays. Due to its industry leading small Light Emitting Surfaces (LES), the COB array is very easy work with and will enable easier and less expensive designs. All LUXEON COBs are available in a single 3-step as well as a single 5-step MacAdam Ellipse, ensuring uniform optical performance in the application. Ideal applications include down lights and directional lamps.

Mounting indicator marks overview

MechaTronix recommends the use of a high thermal conductive interface between the LED module and the LED cooler. Either thermal grease, a thermal pad or a phase change thermal pad thickness 0.1-0.15mm is recommended. Thermal pads or phase change thermal pads can be pre-applied from MechaTronix.



Luxeon COB 1208

Model names

- Luxeon COB LHC1-xxxx-1208

Mounting

- Direct mounting with 2 self tapping screws M3 x 6mm
 Red indicator marks
- With Zhaga Book 3 LED holder
 BJB spotlight connector 47.319.2011
 Ideal Industries Chip-Lok™ holder 50-2100SH
 TE Connectivity Lumawise type Z50 2213130-1
 TE Connectivity Lumawise type Z50 2213130-2
 Mounting with 2 self tapping screws M3 x 8mm
 Green indicator marks




Luxeon COB 1211

Model names

- Luxeon COB LHC1-xxxx-1211

Mounting

- With Zhaga Book 3 LED holder
 BJB spotlight connector 47.319.2033
 Ideal Industries Chip-Lok™ holder 50-2204CT
 Mounting with 2 self tapping screws M3 x 8mm
 Green indicator marks



Luxeon COB 1216

Model names

- Luxeon COB LHC1-xxxx-1216

Mounting

- With Zhaga Book 3 LED holder
 BJB spotlight connector 47.319.2033
 Ideal Industries Chip-Lok™ holder 50-2204CT
 Mounting with 2 self tapping screws M3 x 8mm
 Green indicator marks

